



Master Code _ _ _ _ _

Technician Name _____

How to arm the system in the Away Mode.

- Close all sensors (i.e. windows and doors). The Ready indicator should be on.
- To arm, press **Exit** key or enter your four or six digit user code to arm the system.
- The armed icon will turn on.
- You will have _____ seconds to leave the premises.

How to arm the system in the Stay Mode.2

- Close all protected doors and windows.
- Enter your four or six digit user code.
- Press the **Stay** key.

How to disarm the system.

- Enter your user code to disarm the system anytime it is armed.
- If your code is not valid, the system will not disarm and a two-second error tone will sound. If this happens, try again.

How to reset the smoke detector.

- Enter ***7**, this will reset all smoke detectors (your system must be disarmed to use the reset function).
- If the smoke detectors have gone off, you will need to do this before you can arm the system again.

How to set the date on the keypad.

- Enter ***96** followed by the master code.
- Enter the **Day of Week**. 1=Sunday, 2=Monday, 3=Tuesday, 4=Wednesday, 5=Thursday, 6=Friday, and 7=Saturday.
- Enter the **Month Code**.

01 = January	04 = April	07 = July	10 = October
02 = February	05 = May	08 = August	11 = November
03 = March	06 = June	09 = September	12 = December
- Enter the **Day Code**. Must always be two digits. Example: The 5th would be entered as 05.
- Enter the last two digits of the Year Code. Example: For 1997 enter 97.--

How to set the system clock.

- Press ***97** followed by the master code.
- Enter the **Hour Code** which must be two digits.

12 a.m. = 00	6 a.m. = 06	12 p.m. = 12	6 p.m. = 18
1 a.m. = 01	7 a.m. = 07	1 p.m. = 13	7 p.m. = 19
2 a.m. = 02	8 a.m. = 08	2 p.m. = 14	8 p.m. = 20
3 a.m. = 03	9 a.m. = 09	3 p.m. = 15	9 p.m. = 21
4 a.m. = 04	10 a.m. = 10	4 p.m. = 16	10 p.m. = 22
5 a.m. = 05	11 a.m. = 11	5 p.m. = 17	11 p.m. = 23
- Enter the Minutes Code which must be two digits. Example: 7 minutes after would be entered 07.

How to bypass one or more zones (To turn off a selected area of the house, while still protecting the rest of the home).

- Press the **Bypass** key.
- Enter the zone you wish to bypass.
- Press the **Bypass** key again to confirm.
- Press the **#** key to exit the Bypass Mode.

